Data sheet HP LaserJet Managed E40040dn



Small and mighty: HP's smallest Enterprise printer

HP Managed MFPs and printers are optimised for managed environments. With increased monthly page volumes and fewer interventions, this portfolio of products can help reduce printing and copying costs. See your HP Authorized Reseller for details.





This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: http://www.hp.com/learn/ds

Easy to use, simple to manage

- HP FutureSmart firmware can be updated with the latest features¹ to optimise your investment for years to come.
- Centralise control of your printing environment with HP Web Jetadmin and help build business efficiency.²
- Easily enable workflows across your fleet with a consistent user experience and intuitive, tablet-like icons.
- Set up this printer fast, and easily manage device settings to help increase efficiency.

The world's most secure printing³

- The operating code (BIOS) is automatically checked during startup and repairs itself if compromised.
- Common Criteria certified⁴ to continually monitor memory activity to detect and stop attacks in real time.
- Firmware is automatically checked during startup to determine if it's authentic code digitally signed by HP.
- The printer's outgoing network connections are inspected to stop suspicious requests and thwart malware.
- Safeguard data stored on this printer keys, passwords, certificates, and more with the embedded HP Trusted Platform Module. 5

Enhanced productivity to empower work teams

- Give workgroups what they need to succeed with hundreds of HP and third-party solutions and card reader support.
- Help ensure the security of confidential information with PIN/Pull printing to retrieve print jobs.
- Stay connected with an optional accessory for wireless,⁶ Bluetooth[®] Low Energy, and NFC touch-to-print.
- Print directly from the 6.9 cm (2.7 inch) colour display.

Sustainability is smart business

- Help save paper right out of the box. Two-sided (duplex) printing is set at default for automatic savings.⁷
- Help reduce wasted paper and toner by only printing jobs that are truly needed, using HP Roam for ${\rm Business.}^8$
- Save energy without sacrificing performance this printer is ENERGY STAR[®] and Blue Angel certified.
- Remove barriers and help meet compliance and accessibility standards with the HP Accessibility Kit (which includes Braille overlay and tactile adhesives, an HP Access Handle, and BigKeys LX Keyboard) and compatibility with HP Accessibility Assistant.

Product walkaround

HP LaserJet Managed E40040dn shown

- 1.150 sheet output bin
- 2. Front door, access to Original HP toner cartridges with JetIntelligence
- 3. Automatic two-sided printing (default)
- 4. 100 sheet multipurpose input tray 1
- 5.250 sheet input tray 2
- 6. 6.9 cm colour graphics display
- 7. Convenient front on/off switch
- 8. Right door, access to print path
- 9. Hi-Speed USB 2.0 port for third-party devices
- 10. Hi-Speed USB 2.0 printing port
- 11. Gigabit Ethernet network port



Accessories, Supplies and Support

Supplies	W9024MC HP Black Managed Original LaserJet Toner Cartridge (~11,500 pages)
Accessories	3JN69A HP Jetdirect 3100w BLE/NFC/Wireless Accessory
	4QL32A HP Legic Secure USB Reader
	8FP31A HP Jetdirect LAN Accessory
	8ZN00A HP HIP2 Card Reader Accessory Kit
	D9P29A HP LaserJet Pro 550-sheet Feeder Tray
	X3D03A HP USB Universal Card Reader
	Y7C05A HP HIP2 Keystroke Reader
Service and Support	U11Y1E HP 3 year Next Business Day LaserJet Managed E40040 service U11Y2E HP 4 year Next Business Day LaserJet Managed E40040 service U11Y3E HP 3 year Channel Parts Only LaserJet Managed E40040 service U11Y7E HP 3 year Channel Parts Only LaserJet Managed E40040 service U11Y8E HP 4 year Channel Parts Only LaserJet Managed E40040 service U11Y9E HP 5 year Channel Parts Only LaserJet Managed E40040 service U11Y9E HP 5 year Channel Parts Only LaserJet Managed E40040 service U11Y9E HP 1 year Post Warranty Next Business Day LaserJet Managed E40040 service U11YGPE HP 2 year Post Warranty Next Business Day LaserJet Managed E40040 service U11YGPE HP 1 year Post Warranty Channel Parts Only LaserJet Managed E40040 service U11YGPE HP 2 year Post Warranty Channel Parts Only LaserJet Managed E40040 service U11YFPE HP 2 year Post Warranty Channel Parts Only LaserJet Managed E40040 service

Technical specifications

M - d-1	
Model	HPLaserJet Managed E40040dn
Product number	39235A
Functions	Print
Control panel	6.85 cm Color Non-Touch Control Panel with 24 Keypad
Print	
Print technology	Laser
Print speed ¹	Black (A4, normal): Up to 38 ppm (default); Up to 40 ppm (HP High Speed Mode) ; Black (A4, duplex): Up to 31 ipm
First page out ²	Black (A4, ready): As fast as 6.5 sec ; Black (A4, sleep): As fast as 8.8 sec
Print resolution	Black (best): Up to 1200 x 1200 dpi ; Technology: 300 dpi, 600 dpi, HP FastRes 1200, HP ProRes 1200
Monthly duty cycle	Up to 120,000 pages A4; Recommended monthly page volume: 1,500 to 7,500 pages
Printer smart software features	Print preview, duplex printing, print multiple pages per sheet (2, 4, 6, 9, 16), collation, watermarks, store print jobs, easy-access USB
Standard print languages	HP PCL 6, HP PCL 5, HP PostScript level 3 emulation, native PDF printing (v 1.7), Apple AirPrint™
Fonts and typefaces	105 internal TrueType fonts scalable in HP PCL, 92 internal scalable fonts in HP PostScript Level 3 emulation (Euro symbol built-in); 1 internal Unicode Fonts (Andale Mono World Type); 2 Internal Windows Vista 8 Fonts (Calibri, Cambria); additional font solutions available via third-party flash memory cards; HP LaserJet Fonts and IPDS Emulation available at Http://www.hp.com/go/laserjetfonts
Print area	Print margins Top: 2 mm, Bottom: 2 mm, Left: 2 mm, Right: 2 mm; Maximum print area : 212 x 352 mm
Duplex printing	Automatic (default)
Processor speed	800MHz
Connectivity	
Standard	1 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network
Optional	HP Jetdirect LAN Accessory 8FP31A; HP Jetdirect 3100w BLE/NFC/Wireless Accessory 3JN69A
Mobile printing capability ³	The Pacinet CharAccessory of a second control of the end of the en
	The entry opportunity indication to the provided and the entry of the
Supported network protocols	Via Outcomment was additioned to the provide was a comment of the provide of the
Network capabilities	res, via ne y educe a triente entreuende print server (standard winch supports, robase-is, robosse-is, ouc.saz (ecc) support on rast entented and og clinks, in-sec (standard winch supports), robase-is, robosse-is, robosse-is, ouc.saz (ecc) support on rast entented and og clinks, in-sec (standard winch supports), robase-is, robosse-is, robosse-is
Hard disk	Not Applicable to this product
Memory	Standard: 1 GB;Maximum: 1 GB
Media handling	
Number of paper trays	Standard: 2: Maximum: 3
Media types	Paper (plain, EccEFFICIENT, linkt, heavy, bond, coloured, preprinted, prepunched, recycled, rough); Envelopes; Labels
Media size	Custom (metric): Tray 1: 76 x 127 to 216 x 356 mm; Tray 2: 105 x 148 to 216 x 356 mm; Optional Tray: 105 x 148 to 216 x 356 mm; Supported (metric): Tray 1: A4, RA4, A5; B5 (JIS); B6 (JIS); 10 x 15 cm, A6, 16K, envelopes: (B5, C5, ISO, C6, DL ISO); Custom: 76 x 127 to 216 x 356 mm; Tray 2: A4; RA4, A5; B5 (JIS); B6 (JIS); A6; T6K; 105 x 148 to 216 x 356 mm; Optional Tray: 105 x 148 to 216 x 356 mm; Optiona
Media handling	Standard input: 100 sheet tray 1,250 sheet input tray 2 Standard output: 150 sheet output 2 phional tinput: Optional third 550 sheet tray. All trays include fixed-size paper tray quides
Media weight	Surround input into since tray 1, 20 since input ray 2, advance output into since output on optional input of optional input roles, tray 3, advance investigations and a since into 3, advance into 3, advance input roles of advance input roles of advance into 3, advance into3, advance in
Input capacity	Tray 1:Sheets: 100; Envelopes: 10 Tray 2: Sheets: 250 Tray 3: Sheets: 550 (optional) Maximum: Up to 900 sheets (with Optional 550 sheet tray)
Output capacity	Standard: Up to 150 sheets Envelopes: Up to 10 envelopes Maximum: Up to 150 sheets
Compatible operating systems	Windows 11; Windows 10; Windows 8.1; Windows 7; Windows Client OS; Android; iOS; Mobile OS; macOS 10.12 Sierra; macOS 10.13 High Sierra; macOS 10.14 Mojave; macOS 10.15 Catalina
Compatible network operating systems	Windows 11; Windows 8; Windows 7; Windows Server; Linux; Citrix; UNIX
Minimum system requirements	Windows: 2 GB available hard disk space Internet connection or USB port Internet browser. For additional OS hardware requirements see http://www.microsoft.com Mac: 2 GB available hard disk space Internet connection or USB port Internet browser. For additional OS hardware requirements see http://www.apple.com
Software included	No software solutions are included in the Box only on http://www.hp.com or http://www.123.hp.com
Security management	Identity management: Kerberos authentication, LDAP authentication, 1000 user PIN codes, Optional HP and 3rd party advanced authentication solutions (e.g., badge readers); Network: IPsec/firewall with Certificate, Pre- shared Key, Kerberos authentication, Supports WIA-10 IPsec configuration Plug-in, 802.1X authentication (EAP-PEAP; EAP-TLS), SNMPv3, HTTPS, Certificates, Access Control List; Data: Storage Encryption, Encrypted PDF & Email (uses FIPS 140 validated cryptographic libraries from Microsoft), SSL/TLS (HTTPS), Encrypted (redentials; Device: HP Sure Start Secure Boot (BIOS Integrity Checking with self-healing capability), Intruson Detection (Constant in-device monitoring for attacks), Whitelisting (loads only known good code), Embedded Trusted Platform Module, HP Connection Inspector, Security lock slot, USB port disablement; Security ymanagement: Compatible with HP JetAtVantage Security Manage, Device Rescurity System (Ressage snocessed and accessible in Arcsight and Splunk SIEMs
Printer management	HP Printer Assistant, HP Web JetAdmin Software, HP JetAdvantage Security Manager, HP SNMP Proxy Agent (Part of HP WebJetAdmin), HP WS Pro Proxy Agent (Part of HP WebJetAdmin), Printer Administrator Resource Kit for HP Universal Print Driver (Driver Configuration Utility – Driver Deployment Utility – Managed Printing Administrator)
Dimensions and weight	
Printer dimensions (W x D x H)	Minimum 381 x 357 x 220 mm; Maximum: 381 x 781 x 241 mm (printer fully opened)
Printer weight	~8.5 kg
Operating environment	Temperature: 15 to 32.5°C Humidity: 10 to 90% RH
Storage conditions	Temperature -20 to 40°C
Acoustics	Acoustic power emissions: 6.5 B(A) at 38 ipm Acoustic pressure emissions: 54 dB(A) at 38 ipm
Power	Requirements: 220-volt input voltage: 220 to 240 VAC (+/- 10%), 50/50Hz (+/- 3 Hz); Consumption: 531 watts (active printing), 8.1 watts (ready), 1.2 watts (sleep), 0.07 watts (auto-off/manual-on), 0.07 watts (manual off); Typical Electricity Consumption (TEQ ¹⁴ ; Blue Angel: 1.189 kWh/week; Energy Star 3.0: 0.462 kWh/week; Power supply type: Internal (built-in) Power Supply
Energy savings feature technology	HP Auto-On/Auto-Off Technology; Instant-on Technology
Certifications ⁵	TUV and GS Mark (Germany): Eastern European country approvals; CE Marking: Other Safety & EMC Certification approvals as required by individual countries. Electromagnetic emission standard (LSPR 22:2008 (International) Lass A, CISPR 32:2012 (International)/ EN 55032:2012, CISPR 35:2016 (International)/ EN 55035:2017, EN 55024:2010+A1:2015, EN 61000-3-2:2014, EN 61000-3-2
	Mercury-free
Sustainable impact specifications	Herculy-free
Sustainable impact specifications Country of origin	Made in Philippines

Footnotes

¹ Some features enabled by future HP FutureSmart firmware upgrades may not be available on older devices, if for example, physical product characteristics limit the functionality of the new feature. ² HP Web Jetadmin is free and available for download at http://www.hp.com/go/webjetadmin.

³ HP's most advanced embedded security features are available on HP Managed and Enterprise devices with HP FutureSmart firmware 4.5 or above. Claim based on HP review of 2019 published features of competitive in-class printers. Only HP offers a combination of security features to automatically detect, stop, and recover from attacks with a self-healing reboot, in alignment with NIST SP 800-193 guidelines for device cyber resiliency. For a list of compatible products, visit http://www.hp.com/go/PrinterSThatProtect. For more information, visit http://www.hp.com/go/PrinterSthatProtect.

⁴ Third-party certification based on Common Criteria Information Technology Security Evaluation ISO/IEC 15408 Standard requirements as of May 2019. Certification applicable to HP Managed and Enterprise devices running HP FutureSmart Firmware version 4.5.1 and later. For more information: https://www.commoncriteriaportal.org/files/epfiles/Certification%20Report%20-%20HP%20Intrusion%20Detection.pdf.

⁵ Use of the HP Trusted Platform Module may require a firmware upgrade.

⁶ Wireless performance is dependent on physical environment and distance from access point and may be limited during active VPN connections.

⁷ Dependent upon country setup specifications.

⁸ To enable HP Roam, some devices may require firmware to be upgraded and an optional accessory to add Bluetooth® Low Energy (BLE) beaconing capabilities. Subscription may be required. For more information, visit http://www.hp.com/go/roam.

Technical specifications disclaimers

¹ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/qo/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity

² Measured using ISO/IEC 17629. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ³ To enable HP Roam, some devices may require firmware to be upgraded and an optional accessory to add Bluetooth® Low Energy (BLE) beaconing capabilities. Customers can purchase the HP Jetdirect 3100w BLE/NFC/Wireless

accessory or the RadBeacon USB. Subscription may be required. For more information, visit http://www.hp.com/go/roam.

⁴ Typical Electricity Consumption (TEC) rating represents the typical electricity consumed by a product during 1 week, measured in kilowatt-hours (kWh).
⁵ EPEAT® registered where applicable. EPEAT registration varies by country. See http://www.epeat.net for registration status by country.

⁶ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115V device and 230V for Blue Angel.

⁷ Value is confirmed For yield information on the cartridge included with your printer, see http://www.hp.com/go/toneryield.Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors.

© Copyright 2022 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. gb-en May 2022

